



DESCRIPTION

The **CBS ArcSafe® RSA-187C** allows technicians to remotely close or open the General Electric J-Line molded case circuit breakers (MCCBs) from a safe distance while remaining stationed outside of the arc-flash boundary. Installation and operation does not require any modifications to the existing electrical equipment. The RSA-187C is compatible with all type 600A frame size THJK, TJ, TJC, TJD, TJJ, TJK, and TJL General Electric J-Line MCCBs. Typical applications of these circuit breakers include switchboards, motor control centers, and lighting, power, and customized control panelboards. The CBS ArcSafe RSA-187C is a cost-effective solution for keeping operators safe when compared to other arc-flash mitigation alternatives.

SPECIFICATIONS

WEIGHT:	13 lbs
DIMENSIONS:	7.5"H x 14"W x 4.5"D
POWER CONSUMPTION:	30W
OPERATING DISTANCE:	25-300 feet
COMPATIBILITY:	General Electric J-Line Molded Case Circuit Breaker (600A frame size, types THJK, TJ, TJC, TJD, TJJ, TJK, and TJL)
CONTROL/POWER SOURCE:	CBS ArcSafe® RSO-I AR Control Console

OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup, no equipment modification required
- Quick installation and removal from gear
- Adjustable travel and locators to accommodate entire product line
- Reduces or eliminates need for arc-flash hazard suits
- Eliminates all hazardous manual contact with gear during operation
- Designed, manufactured, and assembled in the USA

